


THUNDERPUSS


FX TYPE: Boost

Based on the Jack Orman Mosfet Boost

© 2016 madbeanpedals



1.31" W x 1.1" H



Etcher's Paradise projects are intended for DIY use only! Commercial pedal manufacturing using these materials is strictly forbidden.

B.O.M.					
Resistors		Caps		Diodes	
R1	10M	C1	1n	D1	9.1v Zener
R2	2k7	C2	47pF	D2	1N5817
R3	2k7	C3	100uF	Transistors	
R4	62k	C4	100n	Q1	BS170
R5	100k	C5	100uF	Pots	
R6	4k7	C6	10uF	GAIN	5kC
		C7	100n		

Shopping List			
Value	QTY	Type	Rating
2k7	2	Metal / Carbon Film	1/4W
4k7	1	Metal / Carbon Film	1/4W
62k	1	Metal / Carbon Film	1/4W
100k	1	Metal / Carbon Film	1/4W
10M	1	Metal / Carbon Film	1/4W
47pF	1	Ceramic	16v min.
1n	1	Film	16v min.
100n	2	Film	16v min.
10uF	1	Electrolytic	16v min.
100uF	2	Electrolytic	16v min.
9.1v Zener	1		1/2 or 1W
1N5817	1		
BS170	1		
5kC	1	Solder Lug	9 or 16mm

1590A Drill Guide

3.62"W x 5.73"H

